# Honeywell

# **SOUNDBAR**

Owner's manual

Please read the manual carefully before use



Secure Connection Limited Flat C 61/F, Block A, LA Rossa Coastal Skyline 12 Tung Chung Water Front Road Tung Chung

support@honeywellconnection.com manufacturers | Connection Ltd. |
Web: www.honeywellconnection.com rights reserved.

The Honeywell trademark is used under license from Honeywell International Inc. Honeywell International Inc. makes no representations or warranties with respect to this product. This product is manufactured by Secure Connection Limited. Hone Kona.

All trade names are registered trademarks of respective manufacturers listed. ©2021 Secure Connection Ltd., Hong Kong, All rights reserved.

Honeywell

www.honeywellconnection.com info@honeywellconnection.com

Dear Customer.

Thank you for purchasing Honeywell Suono P1000 Soundbar.

In order to facilitate the installation and use of this Multifunctional Soundbar, we recommend that you carefully read this manual, and keep it stored safely. To ensure that you always enjoy quality sound, please use this manual for proper use and maintenance of your product.

If any questions arise during use, please consult this manual. If it is in accordance with the warranty, we kindly welcome you to contact us at:

#### support@honeywellconnection.com

We welcome any comments or suggestions you may have about our products and service.

# **Contents**

1.	What's in the Box	01
2.	Performance Index	01
3.	Product Appearance and Structure	02
4.	Function Description	02
5.	Remote Control	03
6.	How to Operate	03
6.1.	Charging	03
6.2.	Powering on	03
6.3.	Pairing via Bluetooth	03
6.4.	3.5mm AUX Cable Operation	04
6.5.	USB Function	04
6.6.	HDMI/ARC Operation	04
6.7.	Digital Optical Operation	04
7.	Precaution for Use	05
8.	Troubleshooting	05

# What's in the Box

- 1. Suono P1000 Soundbar: 1 Unit
- 2. DC Power Adapter: 2 Units
- 3. Remote Control: 1 Unit
- 4 User Manual: 1 Unit
- 5. Warranty Card: 1 Unit

# Performance Index


Product Name	Suono P1000 Soundbar
Audio Interface	Bluetooth 3.5mm AUX USB HDMI/ARC Digital Optical
Charging Interface	DC input
Output Power	15W*2
Rated Voltage	18V/2A
Bluetooth Version	v5.0
Bluetooth Range <sup>1</sup>	10 meters
Battery Type and Capacity	N/A (wired power cable)
Driver Size <sup>2</sup>	52mm*2
Frequency Range	20Hz-20KHz
Signal To Noise Ratio <sup>3</sup>	≥85db
Impedance <sup>4</sup>	6 Ohms
Product Dimension	80*6*6cm
Product Weight	1.25Kg

The Bluetooth Range can vary depending on the ambient environment. The range is sitested in an outdoor environment with no physical obstacles.

<sup>2.</sup> Driver size denotes the diameter of the diaphragm.
3. Signal to Noise Ratio is defined as the ratio of signal power to the noise power, it is represented in decibels.

<sup>3.</sup> Impedance refers to the load a speaker places on an amplifier. Technically, impedance is the "resistance" a speaker offers to the current supplied by an amplifier because the output current of an amplifier is AC (not DC, like from a battery), this resistance is called impedance.

# Product Appearance And Structure







Function Description			
Function	What to do		
▶II	Short press to Play/Pause audio*		
ტ/ <b>M</b>	Short press to switch between Bluetooth, AUX, USB, Optical & HDMI/ARC mode		
	Long press to power on/off the device		
<b>▶</b>   /+	Long press to skip to the next track*		
/ ÷	Short press to increase the volume		
◀┫/-	Long press to skip to the previous track*		
-	Short press to decrease the volume		

<sup>\*</sup>Applicable for USB and Bluetooth mode only.

# Remote Control

Button	Function
Ф	Power on/off
MUTE	Mute sound
TREB+	Increase treble
TREB-	Decrease treble
BASS+	Increase bass
BASS-	Decrease bass
VOL+	Increase volume
VOL-	Decrease volume
₩	Next track*
144	Previous track*
M	Play/Pause*
PAIR	To enable Bluetooth pairing
SOURCE	Switch between Bluetooth mode, AUX mode, HDMI mode and Optical cable, USB mode
NEWS	News audio mode
MOVIE	Movie audio mode
MUSIC	Music audio mode

<sup>\*</sup>Applicable for USB and Bluetooth mode only

# Charging

Plug the 15V power adapter into a wall socket and connect the other end of the adapter to the DC input of Suono P1000 Soundbar.

# Powering On

Long press o/M button on the control panel or remote control to power on/off.

# Pairing via Bluetooth

 $Connecting \, any \, Blue to o th \, device$ 

- Press the d/M button on the control panel of the soundbar or the source button on the remote control until Bluetooth mode is enabled. Soundbar is now in Bluetooth pairing mode.
- Open the Bluetooth settings on any Bluetooth device and search for device with name "Suono P1000" and connect.

#### Pairing via Bluetooth (Continued)

#### Note:

- "Suono P1000 Soundbar" will automatically re-pair with the last paired device whenever it is within range.
- Devices with older Bluetooth versions may prompt you to input a passcode key. Please enter "0000" on your device and press OK to successfully connect with "Suono P1000 Soundbar".

#### 3.5mm Aux Cable Operation

- Insert the 3.5mm AUX cable into the AUX input.
- Press the O/M button on the control panel of the soundbar or the source button on the remote control until AUX mode is enabled.
- 3. "Suono P1000 Soundbar" is ready to play audio/music through AUX mode.

#### **USB Function**

When a USB Flash drive is inserted, the audio/music stored in the USB Flash drive will automatically start playing.

#### Note:

- Soundbar is compatible with USB Flash drives up to 32GB in size and supports MP3 and WAV audio formationly.
- The soundbar also has a memory function that will recall and continue from the last-played track whenever a USB Flash drive is reinserted into the soundbar.

# HDMI/ARC Operation

- Connect a compatible device via an HDMI/ARC cable to the HDMI/ARC input on the soundbar.
- 2. Press the **O/M** button on the control panel of the soundbar or the source button on the remote control until HD mode is enabled.
- 3. The soundbar is now ready to use.

# **Digital Optical Operation**

- Connect a compatible device to the digital optical cable input on the soundbar.
- Press the O/M button on the control panel of the soundbar or the source button on the remote control until OP mode is enabled.
- 3. The soundbar is now ready to use.

#### Note:

Ensure Optical SPDIF is selected as the TV's audio output.

# Precaution for Use

- Do NOT use at high volume for any extended period to avoid hearing damage.
- . Do NOT use while driving for phone calls or any other purpose.
- Do NOT use if there is any loud unusual noise. If this happens, please contact
  us at support@honeywellconnection.com.
- This product contains small parts which may be a choking hazard. Not suitable for children under the age of 3.
- This product contains magnetic material. Consult your physician before using the product in case you have a medical implant of any type.
- Do NOT attempt to disassemble this product as this may lead to a hazard and will void the warranty.
- Use this product only with the power supply provided along with this product (applicable for selected models only).
- Do NOT use this product near any form of excessive heat such as gas appliances and heating appliances.

# Troubleshooting

Problem	Solution
No Power	Charge the battery. Connect to the power source.
Unsuccessful Bluetooth pairing	Restart the product and try pairing again.     Disable Bluetooth mode in your device and then re-enable it.
Poor audio quality	Make sure the product is in the Bluetooth range.
Low or no volume	Increase the volume on "Suono P1000 Soundbar" and/or connected device.
Undiscoverable in Bluetooth pairing	The product may be paired to a different device, disconnect from the paired device "Suono P1000 Soundbar" is not in Bluetooth mode, change to Bluetooth mode.

05