Honeywell

SOUNDBAR
Owner's manual
Please read the manual carefully before use

Trueno U4000
Ultimate Series

Honeywell

www.honeywellconnection.com
info@honeywellconnection.com

Dear Customer,

Thank you for purchasing Honeywell Trueno U4000 Soundbar.

In order to facilitate the installation and use of this Multifunctional Soundbar, we recommend that you carefully read this manual, and keep it stored safely. To ensure that you always enjoy quality sound, please use this manual for proper use and maintenance of your product.

If any questions arise during use, please consult this manual. If it is in accordance with the warranty, we kindly welcome you to contact us at:

support@honeywellconnection.com

We welcome any comments or suggestions you may have about our products and service.

Contents

What's in the Box

1. Trueno U4000 Soundbar: 1 Unit
2. Wired subwoofer: 1 Unit
3. Remote control: 1 Unit
4. 3.5mm AUX cable (1.5 meter): 1 Unit
5. Wall mount accessory: 1 Unit
6. AAA Battery: 2 Units
7. User manual: 1 Unit
8. Warranty card: 1 Unit
9. Thank You card: 1 Unit

Performance Index

Product Name	Trueno U4000 Soundbar
Audio interface	Bluetooth 3.5mm AUX USB HDMI/ARC Digital optical
Charging interface	AC input
Output power	240W
Rated voltage	AC 110-240V
Bluetooth version	v5.3+EDR
Bluetooth range[1]	10 meters
Battery type & capacity	N/A (wired power cable)
Driver size[2]	Soundbar: 57mm x 4 Subwoofer: 165.10mm
Frequency range	20Hz-20KHz
Signal to noise ratio[3]	≥ 70dB
Impedance[4]	4Ω*4 + 4Ω*1
Product dimension	Soundbar: L900xH81xD84.7mm Wired Subwoofer: L190xH372x D305mm
Product weight	6.3Kg

1. The bluetooth range can vary depending on the ambient environment. The range is tested in an outdoor environment with no physical obstacles.
2. Driver size denotes the diameter of the diaphragm.
3. Signal to noise ratio is defined as the ratio of signal power to the noise power, it is represented in decibels.
4. Impedance refers to the load a speaker places on an amplifier. Technically, impedance is the "resistance" a speaker offers to the current supplied by an amplifier because the output current of an amplifier is ac (not dc, like from a battery), this resistance is called impedance.

Product Appearance And Structure

Left

Right

Back

Front

Top

Function Description

⏻	Short press to turn power on/off
⮐	Short press to switch between Bluetooth, AUX, USB, Digital optical & HDMI/ARC mode
−	Short press to previous track, long press to decrease volume.
+	Short press to next track, long press to increase volume.
▶ǁ	Shot press to play/pause, long press for 3 seconds to connect/disconnect the Bluetooth device
☼	Short Press to on/off LED light

Remote Control

Button	Function
⏻	Power on/off
MUTE	Mute sound or recover volume
PAIR	Bluetooth mode
INPUT	Switch between Bluetooth, AUX, USB, Digital optical & HDMI/ARC mode
VOL+	Increase volume
VOL-	Decrease volume
▶▶ǀ	Short press for next track, long press in USB mode for fast forward*
ǀ◀◀	Short press for previous track, long press in USB mode for fast backward*
▶ǁ RESET	Short press to play/pause in bluetooth and USB mode, in AUX mode short press to mute/unmute, long press the button to reset the soundbar*
MUSIC	For music EQ effect
MOVIE	For movie EQ effect
NEWS	For news EQ effect
3D	3D effect on/off
TREB+	Increase treble
TREB-	Decrease treble
BASS+	Increase bass
BASS-	Decrease bass

*Applicable for USB and bluetooth mode only
*The Remote uses AAA battery

LED Display	Mode
OPT	Optical mode
BT	Bluetooth mode
ARC	HDMI/ARC mode
USB	USB media mode
AUX	Auxiliary input mode

How to Operate

Please follow the operational guidelines mentioned below.

Powering on

1. Plug the power cable attached with the Trueno U4000 Soundbar into a wall socket.
2. Press the power on/off button on the remote control or soundbar control panel to turn the unit on /off.

Connecting Soundbar to Subwoofer

1. Connect the subwoofer audio cable to SW Output interface on the Trueno U4000 Soundbar.
2. Subwoofer is now paired with the soundbar.

Pairing Via Bluetooth

Connecting any bluetooth device
1. Press the ↻ button on the control panel of the soundbar or the **PAIR** or **INPUT** button on the remote control until bluetooth mode is enabled. Soundbar is now in bluetooth pairing mode.
2. Open the bluetooth settings on any bluetooth device and search for device with name "Trueno U4000" and connect.

Note:
1. "Trueno U4000 Soundbar" will automatically re-pair with the last paired device whenever it is within range.
2. Devices with older bluetooth versions may prompt you to input a passcode key. Please enter "0000" on your device and press OK to successfully connect with "Trueno U4000 Soundbar".

3.5mm Aux Cable Operation

1. Insert the 3.5mm AUX cable into the AUX input.
2. Press the ↻ button on the control panel of the soundbar or the **INPUT** button on the remote control until AUX mode is enabled.
3. "Trueno U4000 Soundbar" is ready to play audio/music through AUX mode.

USB Function

Insert a USB Flash drive, the audio/music stored in the USB Flash drive will automatically start playing.

Note:
1. Soundbar is compatible with USB Flash drives up to 64GB in size and supports MP3 and WAV audio format only.
2. The soundbar also has a memory function that will recall and continue from the last-played track whenever a USB Flash drive is reinserted into the soundbar.

HDMI/ARC Operation

1. Connect a compatible device via an HDMI/ARC cable (not provided with the soundbar) to the HDMI/ARC input on the soundbar.
2. Press the ↻ button on the control panel of the soundbar or the **INPUT** button on the remote control until HDMI mode is enabled.
3. The soundbar is now ready to use.
4. If connecting to TV directly, please ensure your TV supports HDMI/ARC and please connect to TV using the HDMI/ARC port only on the TV.

Note:
Ensure HDMI/ARC is selected as the TV's audio output.

Digital Optical Operation

1. Connect a compatible device to the digital optical cable (not provided with the soundbar) input on the soundbar.
2. Press the ↻ button on the control panel of the soundbar or the **INPUT** button on the remote control until digital optical mode is enabled.
3. The soundbar is now ready to use.

Note:
Ensure optical SPDIF is selected as the TV's audio output.

Equalizer Mode

The soundbar has three equalizer settings tailored for different music styles. press the Music, Movie and News button on the remote control to choose the EQ effect.

LED Light Operation

Short press the ☼ button on the control panel of the soundbar to on/off LED Light.

Precaution for Use

- Do not use at high volume for any extended period to avoid hearing damage.
- Do not use if there is any loud unusual noise. If this happens, please contact us at **support @honeywellconnection.com**
- This product contains small parts which may be a choking hazard. Not suitable for children under the age of 3.
- This product contains magnetic material. Consult your physician before using the product in case you have a medical implant of any type.
- Do not attempt to disassemble this product as this may lead to a hazard and will void the warranty.
- Use this product only with the power supply provided along with this product (applicable for selected models only).
- Do not use this product near any form of excessive heat such as gas appliances and heating appliances.

Troubleshooting

Problem	Solution
No power	• Connect to the power source.
Unsuccessful bluetooth pairing	• Restart the product and try pairing again. • Disable bluetooth mode in your device and then re-enable it.
Poor audio quality	• Make sure the product is in the bluetooth range.
Low or no volume	• Increase the volume on "Trueno U4000 Soundbar" and/or connected device .
Undiscoverable in bluetooth pairing	• The product may be paired to a different device, disconnect from the paired device. • "Trueno U4000 Soundbar" is not in bluetooth mode, change to bluetooth mode.